			<b>FNPW_LSCOMP</b> Pressure Multiplier			<b>FNPW_BKCOMP</b> Pressure Multiplier		
ALOSL (lb/s)	0.017711	(psid)		•		(psid)		
AHISL (Ib/s)	0.015851	20.	01 (	0.7570		20.01	0.6519	
FUEL_BKPT (lb)	0.0000162600	30.	)2 (	0.9577		30.02	0.8444	
MINPW (ms)	0.730	39.	15	1.0000		39.15	1.0000	
		50.	<b>)3</b> '	1.1280		50.03	1.1415	
		54.	<b>96</b> '	1.3780		54.96	1.0449	
		60.	<b>)3</b> '	1.3877		60.03	1.1039	
FNPW_OFFSET		FNPW	FNPW_HSCOMP			FNPW_OFFCOMP		
VBAT	Voltage Offset	Pressu	e M	ultiplier		Pressure	Multiplier	
(volts)	(msec)	(psid)				(psid)		
6	7.611	20.	01 (	0.7149		20.01	0.7149	
8	3.084	30.		0.8756		30.02	0.8756	
10	1.812	39.		1.0000		39.15	1.0000	
11	1.505	50.		1.1304		44.95	1.0621	
12	-	54.		1.1945		50.03	1.1304	
13	1.109	60.	)3 <sup>-</sup>	1.3020		54.96	1.2158	
14	0.970					60.03	1.1638	
15	0.856							

ALOSL "low" injector slope

AHISL "high" injector slope

FUEL\_BKPT Fuel mass at which to switch from low to high injector slope

MINPW Minimum repeatable fuel pulsewidth at 39.15 psid

FNPW\_LSCOMP Multiplier to low slope as a function of injection pressure in psid

FNPW\_HSCOMP Multiplier to high slope as a function of injection pressure in psid

FNPW\_BKCOMP Multiplier to FUEL\_BKPT as a function of injection pressure in psid

FNPW\_OFFSET Injector voltage offset as a function of battery voltage

FNPW\_OFFCOMP Multiplier on FNPW\_OFFSET as a function of injection pressure in psid